

INSTRUCTION SHEET

CLASS 2 TRANSFORMERS

1. Disconnect power supply before beginning installation to prevent electrical shock.
2. Select mounting location and type of mount and mount transformer:
A. Foot Mount: Use screws or bolts through holes in mounting foot. Transformer can be mounted in any position.
B. Multi Mount: Can be mounted to plate or junction box, or can be foot mounted.
3. Determine the proper primary voltage.
Refer to the following chart to select proper wires:

Primary Voltage

120 Volts
208 Volts
240 Volts
277 Volts
480 Volts

Lead Colours

Black & White
Black & Red
Black & Orange
Black & Yellow
Black & Grey

4. Connect secondary (output) connection.
On wire type transformers, be sure to insulate connection to avoid a possible short.
On terminal type transformers, be sure that no exposed wire can come in contact with any terminal.
On multi-output models, use the following chart to determine secondary voltage:

Secondary Voltage

24 Volts
12 Volts
2.5 Volts

Lead Colours

White & Blue
White & Red
White & Orange

5. **Insulation all unused wire(s) to prevent possible short.**
6. Reconnect power supply and check all connections for proper operations.