



# 120 V AC Wireless Smoke Alarm

with LED Safety Light and 10-Year Sealed Battery Backup

Part Number **P4010LACS-WCA** Model **P4010LACS-WCA**  
**10-Year Limited Warranty**



- 10-Year Sealed Lithium Battery** eliminates late night battery chirp
- LED Safety Light** illuminates when alarm sounds to help guide your way to safety
- Voice Notifications**
- Bug Screen** protects alarm from insect ingress
- Flashing LED Status Ring** allows easy identification of current state of alarm



Green:  
Device is Working



Amber:  
Error



Red:  
Danger Detected

## Description

The P4010LACS-WCA is an AC/DC powered smoke alarm with 10 year battery backup that features wireless interconnect capability, enhanced intelligibility for users and an LED safety light that illuminates when the alarm sounds to help guide your way to safety. The voice warning feature accompanies the 85dB tone during an alarm event, and helps reduce confusion with verbal announcements such as "Replace Alarm" at end of alarm life, and "Hush mode activated" when a nuisance alarm is silenced. The three color LED ring helps users quickly determine standby, alarm, or error mode of the alarm.

Kidde P4010 Series Alarms contain 10-year tamper proof batteries that eliminate the need for battery replacement, and ends worry over unauthorized removal. Users are further shielded from late night battery chirps by the unit's Ambient Light Sensing feature, which establishes a day/night cycle and prevents alarm chirping in dark conditions.

Wireless or hardwire interconnect triggers each connected alarm in the network to sound once smoke is detected. This can provide more time to react. Kidde Wireless units can be joined easily with the touch of one button. Existing networks of interconnected alarms can be expanded with use of a single P4010LACS-WCA and additional Kidde Wireless alarms, without the need for a wireless router.

## Features and Benefits

- Wireless (and Hardwire) Interconnect** – Proprietary radio signal joins multiple alarms together, so when one alarm sounds they all sound. User is alerted if an alarm loses connection to the network.
- 120V Direct Wire with 10-Year Sealed-in Lithium Battery Backup** – No battery replacement required over the 10 year life of the alarm.
- LED Safety Light** – Bright LEDs provide lighted escape path.
- Photoelectric Sensor** – Smoke alarm contains advanced photoelectric sensor that may detect visible particles (associated with smoldering fires) sooner than ionization alarms.
- Voice Notifications** – Unit announces "Fire!" and other alerts such as "Replace Alarm," which helps the user better understand the alarm status. Easily switch your language preference (English/French) at any time by pressing the Test button twice on ALL devices you wish to connect.
- Alarm Locate Feature** – Quickly find initiating alarm by silencing other alarms in the network.
- Multi-function One Button Design includes:**
  - Hush® Feature** – Temporarily silences nuisance alarms for up to 10 minutes (smoke must be present before Hush® is activated). End of Unit Life and Network Error chirps can also be silenced.
  - Test Feature** – Simultaneously tests the unit's electronics and verifies alarm operation.



## Architectural and Engineering Specifications

The smoke alarm shall be Kidde model P4010LACS-WCA or approved equal. It shall be powered by 120V AC, 60Hz source with lithium battery backup. The lithium batteries shall be sealed in the unit to prevent removal and/or tampering. The temperature operating range shall be between 4.4°C (40°F) to 37.8°C (100°F) and the humidity operating range shall be up to 95% relative humidity, non-condensing.

The unit shall incorporate an photoelectric smoke sensor with nominal sensitivity of  $2.32 \pm 1.35$  %/ft OBS.

The alarm can be installed on any standard single gang electrical box or a 4" octagon junction box. The electrical connection (to the alarm) shall be made with a plug-in connector. The alarm shall incorporate an activation switch that can be engaged with the included tool or screwdriver to power on the alarm at startup, and deactivate the alarm at end of alarm life.

The P4010LACS-WCA shall include a test button that will simulate fire condition and cause the unit to go into alarm. This sequence tests the unit's electronics to ensure proper operation. A maximum of 24 Kidde devices can be interconnected in a multiple station arrangement. The interconnect system must not exceed the limit of 18 initiating devices, of which 12 can be smoke alarms. With 18 initiating devices (smoke, heat, CO, etc), interconnected, it is still possible to interconnect 6 strobe lights and or relay modules.

The unit shall have audible methods for warning of smoke or fire danger: a piezoelectric horn, rated at 85 decibels at 10 feet, and a voice warning. In an alarm, the horn will sound in the repetitive manner – three long beeps, a 1.5 second pause, three long beeps, repeating. In between, the unit will announce a voice warning, "Fire!". The red LED ring will flash in conjunction with the alarm sound, and the safety light will illuminate.

NOTE : This is not a carbon monoxide (CO) alarm, but will receive and transmit a CO alarm signal (with voice message) from an interconnected CO or combination smoke / CO alarm.

The unit shall incorporate wireless alarm interconnect capability, whereas when one interconnected unit sounds an alarm, all other compatible wireless units in the wireless alarm network will alarm. The maximum distance between wireless interconnect units is greater than 300 feet in open air. The alarm interconnect shall be supervised, where an audible and visual indication is given if the alarm loses connection to other units in the network.

The unit shall at a minimum meet the requirements of CAN/ULC-S531. It shall also include a 10-year manufacturer's limited warranty.

Leading authorities recommend that both ionization and photoelectric smoke alarms be installed to help ensure maximum detection of the various types of fires that can occur within the home. Ionization sensing alarms may detect invisible fire particles (associated with fast flaming fires) sooner than photoelectric alarms. Photoelectric sensing alarms may detect visible fire particles (associated with slow smoldering fires) sooner than ionization alarms.

## Ordering Information

UPC: 0-47871-27349-2


| Part Number   | 12 of 5           | Pack Quantity | Case Dimensions (w x d x h) | Case Weight | Case/Skid |
|---------------|-------------------|---------------|-----------------------------|-------------|-----------|
| P4010LACS-WCA | 100-47871-27349-9 | 3 units       | 22.9cm x 15.2cm x 15.2cm    | 1.54 kg     | 210       |



Kidde Canada Inc.  
P.O. Box 40, Apsley, ON K0L 1A0  
1-800-880-6788  
www.kiddecanada.com

## Technical Specifications

|                           |  |
|---------------------------|--|
| <b>Power Source:</b>      | 120 V AC, 60Hz 53 mA max per alarm with sealed 3V battery backup |
| <b>Sensor:</b>            | Photoelectric  |
| <b>Audio Alarm</b>        | 85 dB at 10 ft   |
| <b>Temperature Range:</b> | 4.4°C (40°F) to 37.8°C (100°F)                                   |
| <b>Humidity Range:</b>    | up to 95% relative humidity, non-condensing                      |
| <b>Size:</b>              | 14.2 cm in diameter x 4.9 cm depth                               |
| <b>Weight:</b>            | 0.27 kg  |
| <b>Wiring:</b>            | Quick connect plug with 15.2 cm (6") pigtails                    |
| <b>Interconnects:</b>     | Up to 24 Kidde devices (of which 18 can be initiating)           |
| <b>Warranty:</b>          | 10-year limited  |



## Installation of Alarm

The smoke alarm should be installed to comply with all local codes having jurisdiction in your area. Make certain all alarms are wired to a single, continuous (non-switched) power line, which is not protected by a ground fault interrupter. A maximum of 305 m (1000') of wire can be used in the interconnect system. Use standard CSA listed household wire (18 gauge or larger as required by local codes).

### Compatible Wireless 10-Year Models

#### 10-Year Sealed Battery Operated Alarms

P4010DCS-WCA: Wireless Smoke Alarm  
P4010LDSCS-WCA: Wireless Smoke Alarm with LED Safety Light  
P4010DCSCO-WCA: Wireless Combination Smoke & CO Alarm

#### Hardwired Alarms with 10-Year Sealed Battery Backup

P4010ACS-WCA: Wireless Smoke Alarm  
P4010LACS-WCA: Wireless Smoke Alarm with LED Safety Light  
P4010ACSCO-WCA: Wireless Combination Smoke & CO Alarm

**Distributed by:**