


Direct Drive Motors

5.0" Direct Drive Motors



Direct Replacement For:

- Coleman • Carrier
- Lennox • York

Part #	HP	Volts	Amps	Cap.	SPD/RPM	Rotation	Body	Bearing	Shaft	Cross
UE-98	1/8	115	5.2	-	3/1050	CCW	3.8"	Sleeve	3.8" x 1/2"	Fasco D178, D356, UE98
M4-R2385	1/5	115	6.5	-	3/1050	CCW	3.9"	Sleeve	5.5" x 1/2"	Fasco D158, UE385, 90
M4-R2429	1/5	208/230	3.2	-	3/1050	CCW	3.9"	Sleeve	5.5" x 1/2"	Fasco D318, UE429
M4-R2679	1/4	115	10.0	-	3/1050	Rev.	4.7"	Sleeve	2.2" x 1/2"	Lennox, York, Carrier
M4-R2368	1/5	115	3.5	4/370	4/1030	CCW	4.5"	Sleeve	3.5" x 1/2"	1268, 024-17903-703, HC37MA135, P8-3789, 90, 3527, 29, 4662, 9662
M4-R2390	1/5	115	3.2	7.5/370	3/1075	Rev.	3.9"	Sleeve	5.5" x 1/2"	UE390, York 24-22489-000, Bohn 5002L, 5003F
M4-R2391	1/5	208/230	1.3	7.5/370	3/1075	Rev.	3.9"	Sleeve	5.5" x 1/2"	Fasco D262, D1016, UE391, 515
M4-R2395	1/4	115	4.9	5/370	3/1075	Rev.	4.1"	Sleeve	4.5" x 1/2"	Fasco D150
M4-R2628	1/4	208/230	1.8	5/370	5/1075	Rev.	4.1"	Sleeve	2.5" x 1/2"	Fasco D151

5.5" Direct Drive Motor Features

- 48 Frame
- 5.5" Diameter
- Open Enclosure
- Mounting: Stud, Strap & Base (Resilient Rings)
- 60 Hz
- Sleeve Bearing
- Shaft: 1/2" x 6.0"
- Reversible
- Permanent Split Capacitor (P.S.C.)
- 60" Coloured Electrical Leads
- Insulation Class B
- Thermally Protected

ROToM
PLUS+

**24 Month
Warranty**



48 Frame - 4 Speed - Multi-HP - Direct Drive

Part #	HP	Volts	Amps	Cap.	SPD/RPM	Rotation	A Dim.	Bearing	Shaft
DD-1314	1/3	115	6.0	7.5/370	4/1075	Revers.	4.40"	Sleeve	1/2"x6"

Cross Reference

Rotom	HP	Voltage	AO Smith	Carrier	Coleman	Emerson	Lennox	ICP	GE	Marathon	Rotom
DD-1314	1/3	115		HC41SE117		11864	P-8-7505	1009045	3583	X003	R43583
	1/4		DL1026	HC41SE121	1486-236P	1863	32663	1008415	3585		R43585
	1/6		DL1036	P257 8583		1864	LFM13				
	1/7			P257 8585							