

Acorn, Selkirk

Acorn Wood Stove 71730867, 2868509042
Selkirk 605850M0

Part #	HP	Volts	Amps	Type	RPM	Rot.	Body	Frame	Bearing	Shaft
HM-R250	1/70	115	0.65	SP/TE	2/1500	CCW	3.5"	3.3"	Sleeve	1.6"x5/16"

HM-R250 Includes 3 prong plug, built in end switch, threaded shaft end with hub.



HM-R1138
illustrated



HM-R1139
illustrated

Buck Stove

Wood Stove R22CCW270ZD, 7163-5967, 7163-6045 (HM-R1138)
Wood Stove R22CW206MD (HM-R1139)

Part #	HP	Volts	Amps	Type	RPM	Rot.	Body	Frame	Bearing	Shaft
HM-R1138	1/50 1/80 1/140	115	.88, .60, .45	SP/ Open	3/1550	CCW	4.0"	3.9"	Sleeve	2.5"x5/16"
HM-R1139	1/50 1/80 1/125	115	.88, .61, .46	SP/ Open	3/1550	CCW	2.8"	3.3"	Sleeve	2.5"x5/16"x1.125"

HM-R1138 Band mounting, HM-R1139 Stud Mounting

R7-RB440
illustrated



R7-RB155
illustrated



R7-RB447
illustrated



R7-RB446
illustrated



R7-RB445
illustrated



Dayton, Grainger

Part #	HP	Volts	Amps	Type	RPM	Rot.	CFM	Frame	Bearing	Comment
R7-RB440	1/125	115	0.25	PSC/ Open	1/3080	CW	50	3.3"	Ball	1TDN7, 4C440
R7-RB155	1/40	115	0.75	PSC/TE	1/2480	CW	148	3.3"	Ball	Grainger 1TDR6, 4C006, Fasco 7021-4933
R7-RB447	1/25	115	0.77	PSC/ Open	1/1640	CW	273	3.3"	Ball	Grainger 4C447, 1TDR3
R7-RB446	1/20	115	0.75	PSC/ Open	1/3120	CW	146	3.3"	Ball	Grainger 4C446, 1TDP7, Fasco 7021-3469, Wood Doctor Furnace
R7-RB445	1/6	115	2.20	PSC/ Open	1/1430	CW	549	3.3"	Ball	1TDT2, 4C445, 4YJ32

R7-RB440 Includes intake screen guard, round discharge - round flange.

Elmira

Elmira Wood Stove 1500, 1600

Part #	HP	Volts	Amps	Type	RPM	Rot.	Body	Frame	Bearing	Shaft
HM-R489	1/60	115	0.72	SP/ Open	3/1300	CW	2.5"	3.3"	Sleeve	3.6"x5/16"x3.5"



Elmira

Wood Stove Blower

Part #	HP	Volts	Amps	Type	RPM	Rot.	CFM	Body	Frame	Bearing
HB-RB34	1/55	115	0.88	SP/ Open	1/3200	CW	100	6.6"	3.3"	Sleeve

HB-RB34 Includes intake screen guard, built-in variable speed control, 3-prong plug, round discharge - large square flange.



Elmira

Elmira (Wood Stove)

Part #	Watts	Amps	Volts	RPM	Rot.	CFM	Blower	Blower Wheel	Bearing
HB-RB200T	35	0.60	115	1600	CCW	200	15"x4.25"x4.25"	65x240mm (2.6x9.4")	Sleeve

HB-RB200T Features 8.3' cord & 3 prong plug



Enviro

Enviro EFW261, EF1000, 1600, 2160, 1200, 1700

Part #	Watts	Amps	Volts	RPM	Rot.	CFM	Blower	Blower Wheel	Bearing
HB-RB261	50	0.80	115	2450	CW	130	16"x4.8"x4.25"	65x240mm (2.6x9.4")	Sleeve

